

IMPORTANT: A TAP is a momentary press; a Hold is a 3-second press!



- Safety Made Simple.

- To activate “PAIR” mode, from any flare in the group, **HOLD** both the power and pi button for **3 seconds**. RED LEDs on all flares in the group will begin to blink.
- **Turning OFF the Flares**
 - There are two ways of turning OFF the flares:
 - To turn off all the flares: Press and **HOLD** the power (round) button for **3 seconds**. All the flares will turn off and a red LED will flash for a few seconds to indicate the flare is turning off.
 - To turn off a single flare: Press and **HOLD** the square *pi* button for **3 seconds**.
- **NEW FEATURE: MAX BRIGHTNESS MODE:**
 - Increase the flare's brightness (reducing flash time to approximately 10 hours).
 - From any flare in the group, while the flares are on, **HOLD** both the power and pi button for **7 seconds**.
 - RED Indicator LED will glow steady. Continue to hold until the GREEN indicator LED turns on. Once GREEN LED turns on, let go of the HOLD.
 - Two Flashes (RED + GREEN LED) = MAX Brightness (~10-15 hours pattern dependent)
 - One Flash (RED + GREEN LED) = Normal Brightness (~17-28 hours pattern dependent)
- **Note: *saves into memory = user preferences are saved when the flares are turned off***

Pi Variables, Inc. dba pi-lit® products are protected by one or more of the following U.S. and foreign patents:

United States:		United Kingdom:	European Community:
8,154,424	10,660,183	3218887	002207837-0001-5
9,847,037	11,013,091	90028382270001	004142503-0001-5
8,564,456	11,706,861	90041425030001-4	3218887
9,288,088	8,157,405	90022078370001-5	
10,536,519	D684,077		
10,443,828	11,725,785		
10,551,014	11,698,186	Italy:	Belgium:
11,162,650	11,769,418	502020000119114	3218887
11,313,546	11,295,625	Sweden:	Switzerland:
D778,752	10,982,987	3218887	3218887
D778,753	9,835,319	Australia:	Germany:
D854,437	D854,438	366289	60 2015 060 604.3
Canada:	Ireland:		
165009	3218887		
Japan:	France:		
6776251	3218887		
7214641	China		
1609250	ZL201880057575.3		
7376475	Additional patents pending:		



CENTER LED INDICATOR

- SOLID RED – Charging
- SOLID GREEN – Fully charged
- BLINKING RED – Pair Mode

POWER + (π) "pi" SIMULTANEOUSLY

TAP – Both simultaneously – Reverse Sequence
Sequence Reversed (saved in memory)

START A NEW GROUP - Enter / Exit Pair Mode

HOLD 3 SECONDS

Center RED LED Blink = Pair Mode On
Center RED LED Off = Pair Mode Off

TOP LEDS (4)

POWER ON - POWER OFF

See below

(π) "pi" BUTTON

See below

16 SIDE LEDS (4 Each side)

* TAP = a momentary press of button
* HOLD = 3 second hold of button

Remember to wait until the flare begins to flash before turning on the next flare in line.

Power Button	(π) "pi" Button
TO TURN ON • PULL OFF CASE - (Rechargeable Lithium only) • TAP Power or (π) "pi" Button (Alkaline batteries) TAP – FOR PATTERN CHANGE FLARE (SAVED INTO MEMORY) • 1- Wave Slow/Smooth Pattern • 2- Rapid March (Quick Flash) • 3- All Flares Flash Simultaneously • 4- Steady Burn	DYNAMIC TILT SENSOR FEATURE (SAVED INTO MEMORY) • TAP 1 – Locks TOP LEDs – 4 Total • TAP 2 – Locks SIDE LEDs – 16 Total • <u>NEW!</u> Tap 3 – Locks TOP + SIDE LEDs - 20 Total • TAP 4 – Return to Dynamic Tilt Sensor Enabled HOLD 3 SEC. – BATTERY STATUS CHECK • IMPORTANT - Flare Must Be Off
Power + (π) "pi" Buttons Simultaneously	Power Off
TAP – REVERSE SEQUENCE • <u>Sequence Reversed (saved in memory)</u> HOLD 3 SEC - ENTER/EXIT PAIR MODE - START A NEW GROUP • <u>Center RED LED Blink = Pair Mode On</u> • <u>Center RED LED not Blinking = Pair Mode Off</u> <u>NEW!</u> HOLD BOTH (π) + POWER BUTTON 5 SECONDS - MAX BRIGHTNESS MODE (ONE FLARE SETS ALL PAIRED FLARES) • <u>Center RED LED STEADY ON - HOLD TILL GREEN LED TURNS ON THEN LET GO</u>	HOLD POWER BUTTON 3 SECONDS • Group Off - Turn off all flares that are grouped together HOLD (π) "pi" BUTTON 3 SECONDS • Individual Flare Off - Turn off that individual flare